

DS-PM1-I1-WB

DS-PM1-I1-WB wireless single input transmitter offers a connection of third party wired detectors like outdoor PIR, to AX PRO alarm system. The alarm types and zone parameters can be set through APP by installers easily, small size design is convenient for installation. Also, transmitter has a feature of detecting device removal by accelerometer application, if someone moves the detector away, an alarm will be reported immediately.



- Small size design, which can be put into wired detector easily
- 433MHz two-way wireless communication
- LED display, show the real status of device
- With one tamper input and one PGM, can be used as zone input or alarm output
- With 3.3v voltage output, can be used to power up external wired detector
- Detection of device removal by accelerometer



▪ Specification

| Model | | DS-PM1-I1-WB |
|-----------------------------------|-----------------------|---|
| Hardware features | Serial port | 1 |
| | Power switch | 1 |
| | Alarm input | 1 Alarm, 1 Tamper |
| | Alarm output | 1 PGM, AM/Output |
| | 3.3v Output | 1, up to 10mA |
| Electrical characteristics | Power supply | 3 CR123 |
| | Operation humidity | 10%~90% |
| | Operation temperature | -10°C ~ 55°C |
| | Power consumption | Quiescent current: 40.29 uA Max current: 47.85mA Voltage: 3 VDC |
| | Battery life span | More than 5 years (report alarm 50 times per day) |
| Wireless transmission | RF frequency | 433MHz |
| | RF method | Two-way communication |
| | RF modulation | 2GFSK |
| | RF distance | 1300m |
| Display | Indicator | 3: Alarm/Tamper (Red) , Fault (Amber) , Signal Strength (Green/Red) |
| General | Installation method | Put inside Wireless Ready Detector |
| | Dimension(WxHxD) | 102*41*20mm |
| | Weight | 35g(Without Battery), 90g(With Battery) |

▪ Available Model

DS-PM1-I1-WB

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,
Hangzhou 310051, China
T +86-571-8807-5998
overseasbusiness@hikvision.com

Hikvision USA
T +1-909-895-0400
sales.usa@hikvision.com

Hikvision Australia
T +61-2-8599-4233
salesau@hikvision.com

Hikvision India
T +91-22-28469900
sales@pramahikvision.com

Hikvision Canada
T +1-866-200-6690
sales.canada@hikvision.com

Hikvision Thailand
T +662-275-9949
sales.thailand@hikvision.com

Hikvision Europe
T +31-23-5542770
sales.eu@hikvision.com

Hikvision Italy
T +39-0438-6902
info.it@hikvision.com

Hikvision Brazil
T +55 11 3318-0050
Latam.support@hikvision.com

Hikvision Turkey
T +90 (216)521 7070- 7074
sales.tr@hikvision.com

Hikvision Malaysia
T +601-7652-2413
sales.my@hikvision.com

Hikvision UK & Ireland
T +01628-902140
sales.uk@hikvision.com

Hikvision South Africa
Tel: +27 (10) 0351172
sale.africa@hikvision.com

Hikvision France
T +33(0)1-85-330-450
info.fr@hikvision.com

Hikvision Kazakhstan
T +7-727-9730667
nikia.panfilov@hikvision.ru

Hikvision Vietnam
T +84-974270888
sales.vt@hikvision.com

Hikvision UAE
T +971-4-4432090
salesme@hikvision.com

Hikvision Singapore
T +65-6684-4718
sg@hikvision.com

Hikvision Spain
T +34-91-737-16-55
info.es@hikvision.com

Hikvision Tashkent
T +99-87-1238-9438
uzb@hikvision.ru

Hikvision Hong Kong
T +852-2151-1761
info.hk@hikvision.com

Hikvision Russia
T +7-495-669-67-99
saleru@hikvision.com

Hikvision Korea
T +82-(0)31-731-8817
sales.korea@hikvision.com

Hikvision Poland
T +48-22-460-01-50
info.pl@hikvision.com

Hikvision Indonesia
T +62-21-2933759
Sales.Indonesia@hikvision.com

Hikvision Colombia
sales.colombia@hikvision.com